



## **DC-DC Step Down** Converters

Model SDC-5 5 Amps

## **Design Features**

- Advanced switch-mode design
- Mount in almost any location
- Compact and light weight
- Reverse polarity protection
- High efficiency
- Cycle by cycle current limiting circuit
- Over voltage protection
- Short circuit protection

## 2 YEAR LIMITED WARRANTY

	MODEL NO.	SDC-5
CAUTION! THERE IS NO ISOLATION BETWEEN THE INPUT AND THE OUTPUT. INPUT AND OUTPUT HAVE A COMMON NEGATIVE		
	INPUT TO OUTPUT ISOLATION	Not isolated. Input and output connections have a common negative
	INPUT VOLTAGE	20 to 32 VDC
VOLTAGE	OUTPUT VOLTAGE	13.8 VDC ± 0.1 V
	OUTPUT VOLTAGE REGULATION	3%
	INPUT CURRENT AT NO LOAD	< 5 mA
OUTPUT CURRENT	CONTINUOUS	5A
OUTPUT CORRENT	CURRENT LIMIT *	5.5A
	OUTPUT RIPPLE AND NOISE	less than 50 mV RMS
ENVIRONMENT	EFFICIENCY	~ 92%
ENVIRONIVIENT	OPERATING AMBIENT TEMPERATURE	- 20° to + 30° C (derate linearly to zero at 70° C)
	HUMIDITY	Max. 95%, non condensing
	OVERLOAD	By current limiting
	OVER HEATING	Drop in output voltage
PROTECTIONS	REVERSE POLARITY	Fuse protection, 5A
	OVER VOLTAGE	Varistor (also protects against load dump)
	INPUT SIDE FUSE	5A (inside the unit)
SAFETY AND EMC	EMISSION	EN50081-1
STANDARDS	IMMUNITY	EN50082-1
STANDANDS	AUTOMOTIVE DIRECTIVE	95 / 45 / EC
	INPUT / OUTPUT CONNECTIONS	Terminal Block - 6.3 mm male flat tab, quick connect
	DIMENSIONS, MM (H X W X D)	48 x 89 x 69
GENERAL	DIMENSIONS, INCHES (H X W X D)	1.9 x 3.5 x 2.7
	WEIGHT, KG	0.17
	WEIGHT, LB	0.4

NOTES:

<sup>1.</sup> Specifications are subject to change without notice
\* In current limit condition, the output voltage will drop if the current drawn increases beyond the current limit value of 5.5 A